



PCT/GB2005/050010.



INVESTOR IN PEOPLE

The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ


BEST AVAILABLE COPY

I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.



Signed

le Behen

Dated

14 February 2005

THE PATENT OFFICE
A
- 4 FEB 2004
NEWPORT

The
Patent
Office

04FEB04 E870573-1 002887
P01/7700 0.00-0402408.9 ACCOUNT CHA

Request for grant of a patent

(See the notes on the back of this form. You can also get an explanatory leaflet from the Patent Office to help you fill in this form)

The Patent Office

Cardiff Road
Newport
South Wales
NP9 1RH

1. Your reference	XA1871		
2. Patent application number (The Patent Office will fill in this part)	0402408.9		04 FEB 2004
3. Full name, address and postcode of the or of each applicant (underline all surnames)	BAE SYSTEMS plc 6 Carlton Gardens London SW1Y 5AD		
Patents ADP number (if you know it)	07914674004 ✓		
If the applicant is a corporate body, give the country/state of its incorporation	United Kingdom		
4. Title of the invention	METHOD FOR REDUCING BIAS ERROR IN A VIBRATING STRUCTURE GYROSCOPE		
5. Name of your agent (if you have one)	BAE SYSTEMS plc Group IP Department Lancaster House, P.O. Box 87 Farnborough Aerospace Centre Farnborough, Hampshire, GU14 6YU		
"Address for service" in the United Kingdom to which all correspondence should be sent (including the postcode)	07914674002 ✓		
6. If you are declaring priority from one or more earlier patent applications, give the country and the date of filing of the or of each of these earlier applications and (if you know it) the or each application number	Country	Priority application number (if you know it)	Date of filing (day / month / year)
7. If this application is divided or otherwise derived from an earlier UK application, give the number and the filing date of the earlier application	Number of earlier application		Date of filing (day / month / year)
8. Is a statement of inventorship and of right to grant of a patent required in support of this request? (Answer 'Yes' if: a) any applicant named in part 3 is not an inventor, or b) there is an inventor who is not named as an applicant, or c) any named applicant is a corporate body. See note (d))	YES		

Patents Form 1/77

Enter the number of sheets for any of the following items you are filing with this form. Do not count copies of the same document

Continuation sheets of this form

Description	14
Claim(s)	03
Abstract	01
Drawing(s)	09 + 9

CP

10. If you are also filing any of the following, state how many against each item.

Priority documents

Translations of priority documents

Statement of inventorship and right to grant of a patent (Patents Form 7/77)

Request for preliminary examination and search (Patents Form 9/77)

1

Request for substantive examination (Patents Form 10/77)

Any other documents (please specify)

11.

I/We request the grant of a patent on the basis of this application.

Signature

Paul B. Rooney

Date

02 February 2004

Paul B. Rooney

12. Name and daytime telephone number of person to contact in the United Kingdom

Maria Burkes 01252 383487

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.

Notes

- If you need help to fill in this form or you have any questions, please contact the Patent Office on 0645 500505.
- Write your answers in capital letters using black ink or you may type them.
- If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.
- If you have answered 'Yes' Patents Form 7/77 will need to be filed.
- Once you have filled in the form you must remember to sign and date it.
- For details of the fee and ways to pay please contact the Patent Office.

30 to the imperfections in the geometry of the vibrating structure. These imperfections cause oscillation of the response mode which is in phase

- 2 -

quadrature (i.e. has a 90° phase relationship) to the motion induced by applied rotation rates, and may be present even when the gyroscope is not rotating. The magnitude of these signals may also be large in comparison to the required in-phase signal which provides the rotation rate information. Recovering the
 5 required rotation induced signal in the presence of a large quadrature signal places stringent requirements on the phase accuracy of the detection system. Accurately phased electronics enable the quadrature signal to be substantially rejected. However practical limitations on the accuracy with which this phasing can be set mean that some of this signal will typically remain to contaminate the
 10 true rotation induced in-phase signal. This limitation is a major source of error for this type of Vibrating Structure Gyroscope.

There is therefore a need for a method for further minimising the impact of quadrature error on vibrating structure Coriolis gyroscope performance.

According to one aspect of the present invention there is provided a
 15 method for reducing bias error in a Vibrating Structure Gyroscope having a vibrating structure, primary drive means for putting the vibrating structure into carrier mode resonance, primary pick-off means for sensing carrier mode motion, secondary pick-off means for sensing response mode vibration of the vibrating structure in response to applied rotation rate, secondary drive means
 20 for applying a force to control the response mode motion, closed loop primary control loops for maintaining a fixed amplitude of motion at the primary pick-off means and for maintaining the drive frequency at the resonance maximum, and secondary control loops for maintaining a null at the secondary pick-off means, in which the ratio SF_{QUAD} over $SF_{IN-PHASE}$ is measured from the secondary
 25 control loop to provide a direct measurement of $\sin(\phi_{SD} + \phi_{PPO})$, according to the relationship;

$$SF_{QUAD} = SF_{IN-PHASE} \times \sin(\phi_{SD} + \phi_{PPO})$$

where SF_{QUAD} is the quadrature scale factor, $SF_{IN-PHASE}$ is the in-phase scale factor, ϕ_{SD} is the phase error in the secondary drive means and ϕ_{PPO} is the
 30 phase error in the primary pick-off means, the total phase error ϕ_E is obtained directly from the measured $\sin(\phi_{SD} + \phi_{PPO})$ according to the relationship;

equal and opposite to the combined effect of the phase errors in the vibrating
30 structure control system.

- 4 -

Conveniently in-phase and quadrature signal components are each multiplied by $\sin \phi_{\text{CORR}}$ and $\cos \phi_{\text{CORR}}$, where ϕ_{CORR} is the phase correction, and the effective phase of each in-phase and quadrature channel adjusted according to the summations

5 $\text{Quadrature}_{\text{CORR}} = \text{Quadrature} \times \cos \phi_{\text{CORR}} + \text{In-phase} \times \sin \phi_{\text{CORR}}$

and

$$\text{In-phase}_{\text{CORR}} = \text{In-phase} \times \cos \phi_{\text{CORR}} - \text{Quadrature} \times \sin \phi_{\text{CORR}}.$$

Advantageously ϕ_{CORR} is adjusted in accordance with operating temperature of the gyroscope to maintain ϕ_E at a minimised value.

10 For a better understanding of the present invention, and to show how the same may be carried into effect, reference will now be made, by way of example, to the accompanying drawings in which;

Figure 1a is a schematic representation of a $\cos 2\theta$ carrier vibration mode not according to the present invention,

15 Figure 1b is a schematic representation of a $\sin 2\theta$ response vibration mode not according to the present invention,

Figure 2 is a schematic block diagram of a conventional control system for a Coriolis Vibrating Structure Gyroscope not according to the present invention,

20 Figure 3 is a schematic block diagram of a digital control system for a Coriolis Vibrating Structure Gyroscope not according to the present invention,

Figure 4 is a schematic block diagram of a digital control system for a Coriolis Vibrating Structure Gyroscope incorporating the ability to adjust the effective secondary drive phase within the software, according to the present invention,

25

Figure 5 is a schematic block diagram of a digital control system for a Coriolis Vibrating Structure Gyroscope incorporating the ability to adjust the effective primary pick-off phase within the software, according to the present invention,

30 The magnitude of the force is given by;

$$F_C = 2MV\Omega_{APP}$$

---- (1)

- 6 -

where M is the modal mass, v is the effective velocity and Ω_{app} is the applied rotation rate. The carrier mode vibration amplitude is typically maintained at a fixed level. This also maintains the velocity, v , at a fixed level and hence ensures that the developed Coriolis forces are directly proportional to the rotation rate, Ω_{app} . The amplitude of the motion induced by these Coriolis forces may be enhanced by accurately matching the resonant frequencies of the carrier and response modes. The motion is then amplified by the Q of the response mode giving enhanced device sensitivity. When operating in an open loop mode the sensitivity (scalefactor) of the gyroscope will be dependent on the Q of the secondary mode, which may vary significantly over the operating temperature range. This dependence may be eliminated by operating the device in closed loop (force feedback) mode. In this mode the induced response mode motion is actively nulled with the applied force required to achieve this now being directly proportional to the rotation rate.

Closed loop operation may typically be implemented using conventional prior art control loops as shown schematically in Figure 2. In Figure 2 the ring shaped vibrating structure 1 is excited into carrier mode resonant motion by a primary drive means 2 which motion is detected by primary pick-off means 3. The signal detected at 3 is demodulated at demodulators 4 prior to application to the carrier mode control loops 5 and re-modulated at re-modulator 6 before application to the primary drive means 2. The carrier mode control loops 5 include a phase locked loop 7 which compares the relative phases of the primary pick-off and primary drive signals and adjusts the frequency of a voltage controlled oscillator 8 to maintain a 90° phase shift between the applied drive and vibrating structure motion. This maintains the motion at the resonance maximum. The primary pick-off signal is also applied to an automatic gain control loop 9 which compares the primary pick-off signal level to a fixed reference level V_0 . The primary drive level is adjusted accordingly in order to maintain a fixed signal level and hence amplitude of motion of the vibrating structure 1 at the primary pick-off means 3.

The response mode motion of the vibrating structure 1 is detected at secondary pick-off means 10. The output signal from means 10 is demodulated

- 7 -

at demodulators 11 to separate the in-phase and quadrature components of this signal with the in-phase component being passed to an in-phase loop 12 and with the quadrature component of this signal being passed to a quadrature loop 13. The in-phase component is that which is at the same phase as the carrier mode motion. The Coriolis forces induced by applied rotation rates will generate motion with both in-phase and quadrature components. The quadrature component is an error term which arises due to the mode frequencies not being precisely matched. Loop filtering is applied to these demodulated base band DC signals by the loops 12 and 13 to achieve the required system performance such as bandwidth etc. The resultant signals are then remodulated at remodulators 14 and summed together by an adder 15 for application to secondary drive means 16 in order to maintain a null at the secondary pick-off means 10. The in-phase baseband signal, which is directionally proportional to the in-phase component of the response mode drive applied to the vibrating structure 1 via the secondary drive means 16 is scaled and filtered at filter 17 to produce a rate output signal 18.

For this mode of operation the scalefactor in response to an applied rotation rate, is given by:

$$SF_{RATE} = \frac{G_B V_O \omega}{k g_{ppo} g_{SD}} \quad \text{---- (2)}$$

where V_O is the primary mode amplitude set level, ω is the primary mode resonance frequency, k is a constant including the resonator dimensions, G_B is the Bryan factor (modal coupling coefficient), g_{ppo} is the primary pick-off gain and g_{SD} is the secondary drive gain.

The Vibrating Structure Gyroscope described in GB 2322196 may also be used in conjunction with a digital electronic control system such as described in GB 2329471. This conventional digital electronic control system is shown in Figure 3 of the accompanying drawings where like components previously described in respect of Figure 2 will be given like reference numerals and not further described in detail. For this implementation signals from the primary and secondary pick-off means 3 and 10 respectively, are digitised directly at

analogue to digital converters 19. The demodulation is then implemented in software 20 for both the in-phase and quadrature channels. The phase locked loop 7 and automatic gain control loop 9 functions are implemented as software functions. A digital control word is generated to drive the analogue voltage control oscillator 8 circuit at the carrier mode resonant frequency which controls the timing of the modulation and drive updates. The loop filters 12 and 13 respectively for the in-phase and quadrature channels of the secondary mode are also implemented in software 20. The drive levels to be applied to the primary and secondary drive means 2, 16 are calculated in the software algorithms and applied via digital to analogue converters 21. The secondary in-phase channel signal is filtered by the output filter 17 to give the appropriate characteristics for the rate output signal 18. In Figure 3 the automatic gain control set level input is shown at 22.

In an ideal case, that is with perfectly phased electronics and identical carrier and response mode frequencies for the vibrating structure 1, there will be no motion detected at the secondary pick-off means 10 when the gyroscope is not rotating. In reality, small geometric imperfections, arising during the gyroscope fabrication process, will give rise to a small splitting of the mode frequencies. This splitting will also tend to fix the angular position of the modes at an arbitrary angle, α , with respect to the primary drive means 2. When α is not equal to 0° the primary drive force will excite both modes to some extent. The phase locked loop 7 will adjust the drive frequency to achieve a 90° phase shift between the applied drive and the vibrating structure motion, as detected by the primary pick-off means 3. However significant motion will exist along the secondary axis which will be predominately in quadrature phase with respect to the primary motion. In a closed loop system this motion will be nulled by a quadrature force component applied by the secondary drive means 16.

The quadrature drive level required to null this signal is referred to as the quadrature bias and is defined as:

30

$$\Omega_{\text{QUAD}} = K \times \Delta F \times \sin 4\alpha$$

---- (3)

30 GB 2322471. Any variation in this signal when the gyroscope is rotated is indicative of a phase error. The origin of this effect is described below.

- 10 -

The phase error, ϕ_E , is measured with respect to the primary resonance motion. The phase locked loop 7 locks on to the primary motion, as measured by the primary pick-off means 2 and provides a logic signal which acts as a reference to control the phasing/timing of the demodulation and re-modulation processes for both the in-phase and quadrature channels. When the gyroscope is rotated a Coriolis force is developed which is in-phase with the primary motion. In a perfect system this force is directly nulled by an in-phase force component applied via the secondary drive means 16. A phase error, ϕ_{SD} , in the secondary drive means 16 will therefore result in some of the signal required to generate the nulling force appearing in the quadrature channel. Similarly, a phase error in the primary pick-off means 3, ϕ_{PPO} , will give rise to an error in the timing of the reference logic signal in the electronics which will propagate into the secondary loops effectively cross-coupling the in-phase and quadrature channels. The secondary pick-off signal is maintained at a null by the force feedback and therefore the accuracy of this phase response is of less concern. A primary drive phase error will result in the primary oscillation frequency being slightly away from the resonance maximum. While this will introduce a small reduction in the drive gain this will not effect the bias as the phasing is referred back to the primary resonance motion. Phase errors in the secondary pick-off and primary drive will not give rise to bias errors and are therefore of less concern.

The rate dependence of the quadrature signal is given by:

$$SF_{QUAD} = SF_{IN-PHASE} \times \sin(\phi_{SD} + \phi_{PPO}) \quad \text{--- (5)}$$

Measurement of the ratio of the in-phase and quadrature scalefactors therefore gives a direct measurement of $\sin(\phi_{SD} + \phi_{PPO})$ from which the total phase error ($\phi_E = \phi_{SD} + \phi_{PPO}$), can be obtained directly. Measurement of the total phase error using this technique has the advantage that it can be performed on a completed gyroscope assembly without the requirement for any additional equipment or mechanical test procedures. The normal calibration procedure for any Coriolis gyroscope requires the assembly to be rotated at a range of known rotation rates on a rate table. This procedure provides a measurement of the

rate scalefactor, SF_{RATE} , and allows this parameter to be adjusted to a pre-set value using well known techniques. Simply recording the data available on the quadrature channel provides a measurement of SF_{QUAD} and hence ϕ_E .

Thus the method of the present invention for reducing bias error in a
 5 Vibrating Structure Gyroscope having a vibrating structure 1, primary drive means 2 for putting the vibrating structure 1 into carrier mode resonance, primary pick-off means 3 for sensing carrier mode motion, secondary pick-off means 10 for sensing response mode vibration of the vibrating structure 1 in response to applied rotation rate, closed loop primary control loops for
 10 maintaining a fixed amplitude of motion at the primary pick-off means 3 and for maintaining the drive frequency at the resonance maximum, and secondary control loops for maintaining a null at the secondary pick-off means 10, includes the steps of measuring the ratio SF_{QUAD} over $SF_{IN-PHASE}$ from the secondary control loop to provide a direct measurement of $\sin(\phi_{SD} + \phi_{PPO})$ according to
 15 the relationship (5) given above where SF_{QUAD} is the quadrature scale factor, $SF_{IN-PHASE}$ is the in-phase scale factor, ϕ_{SD} is the phase error in the secondary drive means 16 and ϕ_{PPO} is the phase error in the primary pick-off means 3. The total phase error ϕ_E is obtained directly from the measured $\sin(\phi_{SD} + \phi_{PPO})$ according to the relationship;

20
$$\phi_E = \phi_{SD} + \phi_{PPO} \text{ as given above}$$

and phase corrections are applied to the secondary drive means 16 and/or primary pick-off means 3 to reduce the phase error ϕ_E and hence the quadrature bias error to enhance the performance of the gyroscope.

When the method of the present invention is used for the gyroscope
 25 having analogue primary and secondary control loops with variable value capacitors (not shown) the phase corrections are applied by varying the values of the variable value capacitors in the secondary control loop relating to the secondary drive means 16 and/or the values of the variable value capacitors in the primary control loop relating to the primary pick-off means 3 to adjust ϕ_{SD}
 30 and/or ϕ_{PPO} such that ϕ_E is minimised in value. Thus as the requirement is for ϕ_E

- 12 -

= 0 this can be conveniently achieved by adjusting either ϕ_{SD} or ϕ_{PPO} provided

$$\phi_{SD} + \phi_{PPO} = 0.$$

Adjustment of ϕ_E is more easily accomplished using the digital electronic control system of GB 2322196. A phase correction can be introduced within the software of the control loop algorithms as shown schematically in Figure 4 where the correction is applied to the secondary drive means 16. Again in Figure 4 parts previously shown in Figures 2 and 3 and previously discussed will be given like reference numerals and not specifically described in further detail. Thus in this context in the method of the present invention when used with a gyroscope having digital primary and secondary control loops the phase corrections equal to ϕ_E are applied to the secondary drive means 16 via the secondary control loop in a manner such as to cross-couple in-phase and quadrature drive channels by an amount equal and opposite to the combined effect of the phase errors in the vibrating structure 1. In the Figure 4 arrangement ϕ_{CORR} is applied to a phase correction unit 24 connected between the remodulators 14 and the adder 15. A further remodulator 23 is located between the voltage controlled oscillator 8 and the automatic gain control filter 9.

This correction can alternatively be applied to the primary pick-off means 3 as shown in Figure 5 in which like components previously described and referenced will be given like reference numerals and not described further in detail. In the Figure 5 arrangement the phase correction unit 24 is located in the primary control loop for application to the primary pick-off means 3 so as to cross-couple in-phase and quadrature drive channels by an amount equal and opposite to the combined effect of the phase errors in the vibrating structure 1. To this end the phase correction unit 24 is located between the quadrature and in-phase demodulators 4 and the phase locked loop filter 7 and automatic gain control loop filter 9 as shown in Figure 5.

The functionality of the phase correction is shown in Figure 6 in which again like features previously described have been given like reference

- 13 -

numerals and will not be further described in detail. An adder 25 and a differencer 26 are included.

When applied on the secondary drive, the in-phase and quadrature components are each multiplied by $\sin\phi_{\text{CORR}}$ and $\cos\phi_{\text{CORR}}$ and the effective phase of each channel adjusted by applying the following summations:

$$\text{Quadrature}_{\text{CORR}} = \text{Quadrature} \times \cos\phi_{\text{CORR}} + \text{In-Phase} \times \sin\phi_{\text{CORR}} \quad \text{--- (6)}$$

$$\text{In-Phase}_{\text{CORR}} = \text{In-Phase} \times \cos\phi_{\text{CORR}} - \text{Quadrature} \times \sin\phi_{\text{CORR}} \quad \text{--- (7)}$$

The gyroscope scalefactor information is conventionally obtained by measuring the uncalibrated gyroscope output over a range of applied rotation rates. A typical data set obtained for the in-phase rate channel is shown in Figure 7. The scalefactor for in-phase is obtained from the slope of the line 27. The equivalent line 28 for the quadrature channel is also shown in Figure 7. The finite slope of line 28 is indicative of a phase error.

The correlation of SF_{QUAD} with ϕ_E is shown in Figure 8. This data was obtained from SF_{QUAD} measurements over a range of values of ϕ_{CORR} . The offset is attributable to a known hardware phase error. The resolution achievable is clearly visible from this graph and indicates that it is possible to set the phase to an accuracy of $<0.05^\circ$. This represents over an order of magnitude improvement in the calibration accuracy of this parameter and is equivalent to a reduction in the contribution of the quadrature bias error, Ω_{Err} , from $0.87^\circ/\text{s}$ to $<0.087^\circ/\text{s}$.

An additional advantage when applying the method of the invention in conjunction with digital control electronics is that it is possible to adjust the phase compensation dependent upon the ambient temperature of the gyro. Coriolis gyroscopes are required to operate over a temperature range of -40°C to $+85^\circ\text{C}$ in typical applications. The phase errors within the hardware are known to vary, in a systematic manner, over this range. The measured variation for a typical automotive sensor is shown in Figure 9. The phase error for this sensor has been corrected, using the method of the present invention, to be approximately zero at room temperature. In any application requiring high

- 14 -

performance it is usual to provide a direct measurement of the sensor ambient temperature. This is typically achieved by incorporating a temperature sensor within, or in close proximity to, the gyroscope. If the temperature variation of the phase error is known then ϕ_{CORR} can be adjusted in accordance with the

5 measured temperature using a simple algorithm function in order to maintain $\phi_E \sim 0^\circ$. For high performance applications it is necessary to characterise the sensor performance over the full operating temperature range. The test procedure involves measurement of the bias and scalefactor at a range of temperatures. The quadrature scalefactor, SF_{QUAD} , may also be readily

10 recorded as part of this procedure to provide the necessary data on the temperature variation of ϕ_E .

CLAIMS

1. A method for reducing bias error in a Vibrating Structure Gyroscope having a vibrating structure, primary drive means for putting the vibrating structure into carrier mode resonance, primary pick-off means for sensing carrier mode motion, secondary pick-off means for sensing response mode vibration of the vibrating structure in response to applied rotation rate, secondary drive means for applying a force to control the response mode motion, closed loop primary control loops for maintaining a fixed amplitude of motion at the primary pick-off means and for maintaining the drive frequency at the resonance maximum, and secondary control loops and for maintaining a null at the secondary pick-off means, in which the ratio SF_{QUAD} divided by $SF_{IN-PHASE}$ is measured from the secondary control loop to provide a direct measurement of $\text{Sin}(\phi_{SD} + \phi_{PPO})$, according to the relationship;

$$SF_{QUAD} = SF_{IN-PHASE} \times \text{Sin}(\phi_{SD} + \phi_{PPO})$$

where SF_{QUAD} is the quadrature scalefactor, $SF_{IN-PHASE}$ is the in-phase scalefactor, ϕ_{SD} is the phase error in the secondary drive means and ϕ_{PPO} is the phase error in the primary pick-off means, the total phase error ϕ_E is obtained directly from the measured $\text{Sin}(\phi_{SD} + \phi_{PPO})$ according to the relationship;

$$\phi_E = \phi_{SD} + \phi_{PPO}$$

and phase corrections applied to the secondary drive means and/or primary pick-off means to reduce the phase error ϕ_E and hence the quadrature bias error to enhance the performance of the gyroscope.

2. A method according to Claim 1, when used with a gyroscope having a silicon vibrating structure.
3. A method according to Claim 2, when used with a gyroscope having a substantially planar, substantially ring shaped vibrating structure.
4. A method according to any one Claims 1 to 3, when used with a gyroscope having analogue primary and secondary control loops with

variable value capacitors, in which the phase corrections are applied by varying the values of the variable value capacitors in the secondary control loop relating to the secondary drive means and/or the values of the variable value capacitors in the primary control loop relating to the primary pick-off means to adjust ϕ_{SD} and/or ϕ_{PPO} such that ϕ_E is minimised in value.

5. A method according to any one of Claims 1 to 3, when used with a gyroscope having digital primary and secondary control loops, in which the phase corrections equal to ϕ_E are applied to the secondary drive means via the secondary control loop in a manner such as to cross-couple in-phase and quadrature drive channels by an amount equal and opposite to the combined effect of the phase errors in the vibrating structure control system.

6. A method according to any one of Claims 1 to 3, when used with a gyroscope having digital primary and secondary control loops, in which the phase corrections equal to ϕ_E are applied to the primary pick-off means by the primary control loop in a manner such as to cross-couple in-phase and quadrature drive channels by an amount equal and opposite to the combined effect of the phase errors in the vibrating structure control system.

7. A method according to Claim 4 or Claim 5, in which in-phase and quadrature signal components are each multiplied by $\sin \phi_{CORR}$ and $\cos \phi_{CORR}$, where ϕ_{CORR} is the phase correction, and the effective phase of each in-phase and quadrature channel adjusted according to the summations.

$$\text{Quadrature}_{CORR} = \text{Quadrature} \times \cos \phi_{CORR} + \text{In-phase} \times \sin \phi_{CORR}$$

and

$$\text{In-phase}_{CORR} = \text{In-phase} \times \cos \phi_{CORR} - \text{Quadrature} \times \sin \phi_{CORR}.$$

- 17 -

8. A method according to Claim 6, in which ϕ_{CORR} is adjusted in accordance with operating temperature of the gyroscope to maintain ϕ_E at a minimised value.
9. A method for reducing bias error in a Vibrating Structure Gyroscope, substantially as hereinbefore described and as illustrated in Figures 4, 5, or 6 as modified or not by Figures 1, 7, 8 or 9 of the accompanying drawings.
10. A Vibrating Structure Gyroscope operated according to the method of any one of claims 1 to 8.


- 18 -

ABSTRACT

METHOD FOR REDUCING BIAS ERROR IN A VIBRATING STRUCTURE GYROSCOPE


5 A method for reducing bias error in a Vibrating Structure Gyroscope having a vibrating structure (1), primary drive means (2), for putting the vibrating structure (1) into carrier mode resonance, primary pick-off means (3) for sensing carrier mode motion, secondary pick-off means (10) for sensing response mode vibration of the vibrating structure (1) in response to applied
10 rotation rate, secondary drive means (16) for applying a force to control the response mode motion closed loop primary control loops for maintaining a fixed amplitude of motion at the primary pick-off means (3) for maintaining the drive frequency at the resonance maximum, and secondary control loops for maintaining a null at the secondary pick-off means (10). In the method the ratio
15 SF_{QUAD} over $SF_{IN-PHASE}$ is measured from the secondary control loop to provide a direct measurement of $\sin(\phi_{SD} + \phi_{PPO})$, according to the relationship $SF_{QUAD} = SF_{IN-PHASE} \times \sin(\phi_{SD} + \phi_{PPO})$ where SF_{QUAD} is the quadrature scalefactor $SF_{IN-PHASE}$ is the in-phase scalefactor, ϕ_{SD} is the phase error in the secondary drive means and ϕ_{PPO} is the phase error in the primary pick-off
20 means. The total phase error ϕ_E is obtained directly from the measured $\sin(\phi_{SD} + \phi_{PPO})$ according to the relationship; $\phi_E = \phi_{SD} + \phi_{PPO}$ and phase corrections applied to the secondary drive means (16) and/or primary pick-off means (3) to reduce the phase error ϕ_E and hence the quadrature bias error to enhance the performance of the gyroscope.

Figure 1b



Response

Figure 1a



Carrier

Figure 2




Figure 4




Figure 5
20




Figure 6




Figure 7






Figure 8



9/9.

Figure 9



**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ BLACK BORDERS
- ☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES
- ☐ FADED TEXT OR DRAWING
- ☐ BLURRED OR ILLEGIBLE TEXT OR DRAWING
- ☐ SKEWED/SLANTED IMAGES
- ☐ COLOR OR BLACK AND WHITE PHOTOGRAPHS
- ☐ GRAY SCALE DOCUMENTS
- ☐ LINES OR MARKS ON ORIGINAL DOCUMENT
- ☐ REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY
- ☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.